

Performance Is Looming

YB Cosworth Power and Ground kit Instructions

The fitting of our Cosworth Power and Ground kit is very simple. But we advise if you re not 100% sure or competent, you consult a qualified automotive electrician.

Firstly remove the battery terminal connections, Negative first.

The old Starter cable can now be removed and replaced with our new cable.

**** This cable is NOT fused, so routing and keeping away from sharp edges is vital! ****

The ground cables can now be replaced,Do not connect to the battery until all cables are replaced.

First longer cable from battery to gearbox (just above the starter motor)

The second shorter cable from battery to chassis (Battery Tray)

Ensure all ground connections are clean.

You can now connect the negative cables to the battery.

LHD Versions have an extra cable to run from battery negative to the engine cam cover area.

Do not hesitate to contact us if you require any further help.

